封面

封底


2m 2.4G BT
AULA
敖马
F75
三模（有线+2.4G+蓝牙）机械键盘
产品手册
Product manual
AULA
敖马
SOGI 斯以特电子
Dongguan Sogai Electronics CO.,LTD
南宫斯奇电子科技有限公司
Made in China
键盘功能说明
Keyboard function description
有线模式/开机 Wired mode / Power on
Switch to [Wired] mode
Connect the Type-C port on the keyboard to the corresponding port on the computer
Connect the USB port on the keyboard to the USB port of the computer
Keyboard ON/OFF Instruction
Turn the switch to wired (no USB power supply), the keyboard will be turned off, and the built-in battery will stop supplying power to the keyboard
2.4G Connection Instruction
Switch to [2.4G] mode
Connect the USB receiver to the USB port of the computer
Wireless receiver
Wireless receiver
Wired mode/Keyboard ON/OFF
Switch to [BT] mode
Connect the Type-C port on the keyboard to the corresponding port on the computer
Bluetooth Connection Instruction
Switch to [BT] mode
Press the combination key Fn + number 1, 2 or 3, the blue light flashes quickly, indicating that the keyboard enters the pairing or search mode. In the connection state, the blue light is on for 5s.
Search for the pairing name "AULA F75 3-mode keyboard" on the BT device, and then it will be BT connected successfully.
Key Combination for Fast Device Switching
Short press
Short press
Short press
Short press
Short press the combination key Fn + number 1, 2 or 3, the blue light flashes quickly, indicating that the keyboard enters the pairing or search mode. In the connection state, the blue light is on for 5s.
Check the battery level of the keyboard, and it can be displayed on the computer when connected to Bluetooth.
Backlight Effect Adjustment
Fn + Combination keys and scroll wheel/arrow keys to switch. 16 RGB light effects and turn off a total of 17 effects.
wave
Follow wave
Dew wave
Leaving footprints
Colorful breathing
Rainbow wave
Rainbow breathing
Turn off
Colorful breathing
Static breathing
Static
raindrops
Static breathing
Static
Flow
Flow
Flow
Flow
Flow
Flow
Flow
Flow
Flow
While the driver driver is enum rhythm RGB lighting effects under this lighting effect, there are 16 lighting effect modes to choose from
Shortcut Key for Backlight Effects Operation
Toggle light mode
Switch light color
Light brightness +
Light brightness -
Light speed +
Light speed -
Shortcut Key Description
Long press Fn + Scroll wheel/arrow keys to switch to the corresponding function
Brightness setting +
Brightness setting -
Speed setting +
Speed setting -
Switch color
Switch light mode
Switch to the corresponding mode
Shortcut Key Description of Small Keyboard
Press Fn+ESC to restore the factory default lighting mode, and the keyboard connected Bluetooth device will not be cleared
In 2.4G/Bluetooth mode, press and hold Fn+8 to check the battery level. When fully charged, the number key 1 to 9 will all light up in white. When the battery is low, the red light flashes slowly (Consumption decreased, and when the battery is low, the red light turns on. Release to restore the light effect).
Fn+0=Android system (the red light of key flashes for 3s) if one single press function and 2 sets Fn combined function.
Key position
Single press
Fn combination
F1
Android
F2
System switch
F3
Mac
F4
Win
F5
Light brightness -
F6
Light brightness +
F7
Play/pause
F8
Previous song
F9
Next song
F10
Mute
F11
Volume -
F12
Volume +
Fn+0=Windows system (the red light of key flashes for 3s) if one single press function and 2 sets Fn combined function.
Key position
Single press
Fn combination
F1
Homepage
F2
Mail
F3
Open explorer
F4
Light brightness -
F5
Light brightness +
F7
Play/pause
F8
Previous song
F9
Next song
F10
Mute
F11
Volume -
F12
Volume +
Fn+0=Mac system (the red light of key flashes for 3s) if one single press function and 2 sets Fn combined function.
Key position
Single press
Fn combination
F1
Search
F2
Dictation
F3
Mission control
F4
Launchpad
F5
Light brightness -
F6
Light brightness +
F7
Play/pause
F8
Previous song
F9
Next song
F10
Mute
F11
Volume -
F12
Volume +
Multifunctional roller adjustment instructions
Dual mode switching Long press the mode button to switch between game and office modes.
Game mode (WIN key & CAPS key, green light flashes 3 times)
Short press the mode button to cycle through 16 lighting effects
Knob clockwise (light brightness +)
Knob counterclockwise (light brightness -)
Office mode (WIN key & CAPS key, the blue light flashes 3times)
Short press the mode button = multimedia
Knob clockwise = multimedia function (volume +)
Knob counterclockwise = multimedia function (volume -)
Current Status Indicator Description
Press and hold Fn to view:
Current connection mode (2.4G, Bluetooth, wired); Current Bluetooth channel; Battery level;
Current system mode (Android, WIN, Mac)
The above corresponding buttons will light up, release the button to restore the light effect.
Description of Smart Sleep Mode
In Bluetooth/2.4G mode, it will automatically enter power-saving mode without any operation for one minute, and lock the button to wake up the keyboard.
Charging Instructions
Connect the keyboard to the computer through the provided USB cable to charge the keyboard. During charging, the charging indicator bar is running. The indicator light is always on after fully charged.
Type-C connectivity is more reliable and performance is more stable.
Charging
Fully charged
Product Parameters
Number of keys: 85 keys
Total board of keys: 4.6mm
Weight: 1100±10g
Product size: 322.7 (L) ×142.2 (W) ×43.1 (H) ±1mm
Product weight: about 975g (excluding wire/receiver)
Net weight: about 1100g (including wire/receiver)
Charging voltage/current: DC 5V, 1A, 150mA
Rated voltage: DC 3.7V (fully charged state: 4.2V)
Rated current: 150mA (fully charged light effect)
1.5 mA (turn off all lights)
Battery life: about 17.5 hours (default lighting effect)
Battery type: 4000mAh 18650 battery
Battery capacity: 4000mAh rechargeable lithium battery
Charging interface: Type-C interface
Computer System Requirements:
Windows system mode: Windows XP, operating system WIN XP, WIN7 WIN8, WIN10 may be required under WinXP and WinVB system)
Mac system mode: MAC computer, Android phone or tablet, IOS phone or tablet with Bluetooth BT3.0, BLEA3, BLEC5 and above hardware.
Wired USB(2.4K) receiver, support hot swap (plug and play).
Description of warranty matters
Dear Customer:
Thank you for purchasing AULA series products! This warranty card is the proof of AULA products, which is kept by the user, with this warranty card you will enjoy the after-sales service provided by AULA. Please read the following terms of this warranty card carefully and keep it in a safe place.
1 With this card you will enjoy the following rights and services:
1 Return service within seven days from the date of sale of the product, if the product has a quality problem, you can choose to exchange or "three packages". In the case of the product appearance and packaging damage, please do not affect the secondary sale of the circumstances, please, with the purchase of the valid certificate, return the product you paid for the purchase price.
2 Within one year, if the product performance failure is detected by AULA after-sales service center within 12 months from the date of purchase, you can enjoy the maintenance service free of charge.
2 The following situations do not belong to the free maintenance scope of this warranty card:
1 Cannot show the valid warranty certificate or the original serial number and the product does not match the warranty card information.
2 There is no serial number on the product or the product model on the warranty certificate does not match the product in kind.
3 Damage and damage caused by abnormal use, maintenance and storage.
4 Failure or damage caused by repair, change or disassembly of the product by a non-authorized maintenance unit without the permission.
5 Failure or damage caused by accidents or other force majeure.
6 Services and additional accessories or gifts outside the product warranty card, AULA has the right to refuse to enjoy the after-sales warranty service.
7 Failure or damage caused by unstable power supply or voltage.
User warranty card
sales record
User name/card
Phone/E-mail
Correspondence address and zip code
sales unit
Sales Unit Address
contact number
zip code
Product Model
Seller's seal
Date of sale
Repair Record
Repair Date
Repair Unit
Telephone number
Address
合格证
QC 01
说明书技术要求：
1.成品尺寸：100x130mm
2.材质：120g铜版纸+打骑马钉
3.工艺：单黑双面印刷